

Triband Mobile Antenna Designing for UMTS/WiMAX/WLAN Applications with High gain

Sonam Parekh¹, Rajeev Mathur²

¹PG Student, Department of Electronics & Communication, Geetanjali Institute of Technical studies, Udaipur, Rajasthan

²Research Scholar, SGVU, Jaipur (Raj.)

Abstract - This paper presents a novel design of a Triband Antenna for wireless communications. Presently many research groups are working on LTE/4G/5G mobile communications technologies and proposed various types of antenna designs. We have proposed an antenna which not only operates at three resonant frequencies but also having high gain. This antenna also fulfills the requirement of low cost, less weight, small size for wireless mobile devices. The design and simulation of proposed triband mobile antenna carried out with Flame Retardant 4 (FR-4) substrate and dimension of antenna substrate is 95mm × 50mm. Performance parameters of this antenna is investigated in terms of Gain, Return Loss, VSWR, radiation pattern. The resonant frequencies of the proposed antenna are 2.45 GHz, 5.09 GHz and 7.65GHz. High Frequency Structure Simulator software HFSS's optometric is used for the proposed antenna for more accuracy and results are optimized. The proposed antenna provides an operating bands, covering the (UMTS) Universal Mobile Telecommunications System bands (2300-2400 MHz), (WLAN) Wireless Local Area Network bands (2400-2497 MHz), and (WiMAX) World Interoperability for Microwave Access system bands (3300-3790 MHz) simultaneously. The simple configuration and low profile attributes of the proposed antenna made it easy to fabrication and suitable for the application in the UMTS/WiMAX/WLAN and satellite communications.

Keywords - UMTS, WiMax, WLAN, Triband Antenna, 4G.

I. INTRODUCTION

In recent years, wireless communication system provides a great interest in an antenna with multiband characteristics for research work. Antennas with small size, low-cost fabrication, light weight, conformability, ease of installation and integration with feed networks have many applications over the broad frequency ranges. This system is having data transfer rate of around 10 times faster than the 3G mobile communication. Now a days due to increasing demand of high spectral efficiency to transfer data in form of video & multimedia it is required to develop such antenna which operates in wide range of frequencies. As per the recent demand, a Triband antenna, for the next generation wireless communication system, is presented in this paper. The proposed antenna provides operating bands, covering the (UMTS) Universal Mobile Telecommunications System bands (2300-2400 MHz), (WLAN) Wireless Local Area

Network bands (2400-2497 MHz), and (WiMAX) World Interoperability for Microwave Access system bands (3300-3790 MHz) simultaneously[1,2].

II. ANTENNA STRUCTURE

Our Main objective is to design an antenna which are having small size and multiband performance characteristics. To design an antenna some essential parameters are required according to transmission line method are-dielectric constant of the substrate (ϵ_r), resonant frequency (f_r), loss tangent(δ) and the height of substrate h . Width and Length of a patch antenna is calculated using standard formulas for the design of microstrip patch antenna[2,3]

(1) Calculation of the width W of antenna, which is given by:

$$W = \frac{v_0}{2f_r} \sqrt{\frac{2}{\epsilon_r + 1}} \quad (1)$$

Where v_0 is the free-space velocity of light.

(2) Calculation of effective dielectric constant, ϵ_{reff} , which is given by:

$$\epsilon_{\text{reff}} = \frac{\epsilon_r + 1}{2} + \frac{\epsilon_r - 1}{2} \left[1 + 12 \frac{h}{W} \right]^{-1} \quad (2)$$

(3) Calculation of the effective length, L_{eff} , which is given by:

$$L_{\text{eff}} = \frac{c}{2f_r \sqrt{\epsilon_{\text{reff}}}} \quad (3)$$

(4) Calculation of the length extension ΔL , which is given by:

$$\Delta L = 0.412h \frac{(\epsilon_{\text{reff}} + 0.3) \left(\frac{W}{h} + 0.264 \right)}{(\epsilon_{\text{reff}} - 0.258) \left(\frac{W}{h} + 0.8 \right)} \quad (4)$$

(5) Calculation of actual length of patch, L which is given by:

$$L = L_{\text{eff}} - 2\Delta L \quad (5)$$

Design of triband antenna based on the basic parameters of resonant frequency $f_r=2.4\text{GHz}$, dielectric constant of FR4 Substrate i.e. 4.4, loss tangent of 0.0002 and thickness of substrate 1.6mm. The design has been simulated by using high frequency structure simulator software (HFSS) which is a full-wave electromagnetic field simulation package with the criterion of return loss S_{11} less than -10dB. The total size of the substrate is 95mm×50mm including ground plane with 65mm×50mm and height of 1.6mm and the size of the

radiated patch is 30mm× 28mm is fed by a microstrip line. Rectangular patch has been investigated for the triple band antennas in the wireless communication systems [4,5].

Design of the proposed antenna structure is shown in Figure 1. Ground plane is kept on the same plane of antenna. The antenna is fed by 50 Ω microstrip line[6,7]. Following are the design specifications for the triband antenna with antenna patch and ground structure:

- Patch width (W) =28mm
- Patch length (L) =30mm
- Ground plane width (W_g) = 50mm
- Ground plane Length (L_g) =65mm
- Dielectric constant 4.4
- Height of substrate (h) = 1.6mm




Fig.1: (a)




Fig.1: (b)

Fig.1: Geometry of Microstrip Patch Antenna

III. RESULTS AND DISCUSSION

The proposed antenna generates three bands at center frequency of 2.45, 5.09 and 7.65 GHz with simulated impedance bandwidth of 0.51, 0.32 and 0.32 GHz respectively. As shown in Figure 2, With reference to the simulation results, we can see that antenna achieve good results.




Fig.2: (a)




Fig.2: (b)

Fig.2: Frequency Response of An Antenna

As it can be seen from the Figure 2 (a), triband antenna exhibits wideband characteristic from 2.12GHz to 2.63GHz, 4.94GHz to 5.26GHz and 7.47GHz to 7.79GHz for $S_{11} \leq -10$ dB threshold level and used for mobile handsets. Practically it is shown above in Figure 2 (b), in which we are getting bands at 2.77, 5.17 upto 6 GHz with one more band which is appearing sometimes at 1.51GHz may be due to practical implementation of design. Practically, we are obtaining a wide band above 5.17GHz




Fig.3: (a)




Fig.3: (b)

Fig.3: VSWR Response of An Antenna

This antenna is able to achieve the desired value of the VSWR of 0.23db for 2.4GHz, 1.86db for 5.09GHz and 2.62db for 7.64GHz as shown in Figure 3 (a). Practically It is shown with values 1.18 at 2.76 GHz and 1.13 at 5.12 GHz




Fig.4: Radiation Pattern Of An Antenna At Fc=2.4GHz

In Figure 4, the simulated radiation patterns at the center frequency $f_c = 2.4\text{GHz}$ are plotted. According to this figure, patch antennas produces a good broadside radiation pattern at 2.4GHz and the peak gain is obtained to be around 26.85dBm.




Fig.5: Radiation Pattern of An Antenna At Fc=5.09GHz

Similarly In Figure 5, the simulated radiation patterns at the center frequency, $f_c = 5.09\text{GHz}$ is plotted and the peak gain is obtained to be around 29.50dBm.




Fig.6: Radiation Pattern of an Antenna At Fc=7.65GHz

As shown above in Figure 6, at frequency $f_c = 7.65\text{GHz}$, we have obtained gain is around 31.17dB.

IV. CONCLUSION

A Triband antenna for wireless communications designed have exhibited a high gain of 26.85dbm,29.50dbm and 31.17dbm for the resonant frequencies of 2.4GHz ,5.09GHz and 7.65GHz respectively. Besides, size of antenna is kept small considering its use in hand held mobile devices. Likewise, the VSWR value of 0.23db, 1.86db and 2.62db is obtained.

Practically band at 1.51GHz is also appearing sometimes, hence we can conclude that if we modify our design than we can get one more band.

This antenna thus is suitable to be used in mobile communication application of (UMTS) (2300-2400MHz), (WLAN) (2400-2497 MHz), and (WiMAX) (3300-3790 MHz) simultaneously (UMTS) Universal Mobile Telecommunications System bands (2300-2400MHz), (WLAN) Wireless Local Area Network bands (2400-2497 MHz), and (WiMAX) World Interoperability for Microwave Access system bands (3300-3790 MHz) simultaneously.

V. REFERENCES

- [1]. Karkkainen,M.K., Meandered multiband PIFA with coplanar parasitic patches," *IEEE Microwave and Wireless Components Letters*, Vol. 15, No. 10, 630(632), 2005).
- [2]. Chi,Y.W. and K.L.Wong, Very-small-size printed loop antenna for GSM/DCS/PCS/UMTS operation in the mobile phone," *Microwave and Optical Technology Letters*, Vol. 51, No. 1,184(192), 2009).
- [3]. Bhatti,R.A.,S.Yi, and S.O. Park ,Compact antenna array with port decoupling for LTE-standardized mobile phones," *IEEE Antennas and Wireless Propagation Letters*, Vol. 8,1430(1433), 2009).
- [4]. Lizzi,L.,Dual-band printed fractal monopole antenna for LTE applications," *IEEE Antennas and Wireless Propagation Letters*, Vol. 10, No. 00, 760(763), 2011).
- [5]. Wong, K.L., G.Y. Lee, and T. W. Chiou, A low-pro le planar monopole antenna for multi-Band operation of mobile handsets," *IEEE Transactions on Antennas and Propagation*, Vol. 51, No. 1, 121(125), 2003).
- [6]. Wong,K.L.andC.H.Huang ,Compact multiband PIFA with a coupling feed for internal mobile phone

- antenna," *Microwave and Optical Technology Letters*, Vol. 50, No. 10, 2487(2491,2008).
- [7]. SEMCAD X by SPEAG, www.speag.com.
- [8]. D.-G.Yang, D.-O. Kim, and C.-Y. Kim, “*Design of Internal Multi-band Mobile Antenna for LTE700/UMTS/WiMAX/WLAN Operation*”(2012).
- [9]. Rajeev Mathur, Sunil Joshi, “Split Ring Array Antenna for WLAN Applications using MIMO Techniques” published in IJCA Special Issue on Evolution in Networks and Computer communications. <http://www.ijcaonline.org/specialissues/encc/number2/326-encc015>. ISBN: 978-93-80864-97-5.
- [10]. Bhaghyashree Sharma, Rajeev Mathur,, “Circularly Polarized Antenna Array Technique for MIMO Application” published in International Journal of Computer Applications (IJCA) October 2015 Edition Digital Library URI : <http://www.ijcaonline.org/archives/volume127/number3/22708-2015906345>, ISBN : 973-93-80889-52-2
- [11]. Rajeev Mathur, Sunil Joshi, “A Novel Multiple Element Patch Antenna for Wireless MIMO Beamforming & WiMAX Applications” presented in “International Conference on Emerging Trends in Networks and Computer Communications (ETNCC-2011), MPUAT, Udaipur” on 22-23 April 2011, Page(s):110 - 114 and published in IEEE Explorer Digital Library. Print ISBN: 978-1-4577-0239-6 DOI: 10.1109/ETNCC.2011.5958497
- [12]. Rajeev Mathur, Dr. Sunil Joshi, “Ultra Wideband Antenna Design & Characteristics: A Review” presented in International Conference organized by “Antenna Measurement & Test Society” and published in proceedings of “AMTS 2011 Ahmedabad” 10-11 Feb 2011.
- [13]. Rajeev Mathur, Sunil Joshi, Krishna C Roy “A Novel Multiband Koch Loop Antenna Using Fractal Geometry for Wireless Communication System AIRCC's International Journal of Wireless & Mobile Networks (IJWMN) Journal, Vol. 3, No. 5, October 2011, PP. 161-172. ISSN : 0975 - 4679 e-ISSN : 0975 – 3834. DOI:10.5121/ijwmn.2011.3203