

INVINCIBELL PLUS GRADE 3

Features	Description
3 Way tamper action	Activation from front, back, and power supply cut off ensures protection from sabotage attempts. In this situation, the siren will activate independently of the control panel.
3mm Poly housing	Enables a panoramic strobe effect illuminating the full bell box
Available as Grade 3	UK specified to Grade 3
Current consumption feature	An incorporated LDR (Light Dependant Resistor) will turn the Deltabell Plus off automatically during daylight hours.
Engineer hold off facility	When first powered with the tamper switch open, the sounder will not activate.
Fully backlit base	The base of the Deltabell Plus is backlit constantly, providing free advertising for your company
Piezo sounders with high decibel output	Belle: 118dBa. Decibell E/ Deltabell E / Deltabell Plus: 104dBA. Note: The Belle has 2 piezos. The Decibell E/Deltabell E/Deltabell Plus have 1 piezo.
Remote engineer hold off	It is possible to disable the bell box tamper when a control panel is in the engineers menu.
Revolving guide holes	Unique leveling mechanism including in-built spirit level and revolving guide holes.
Twin piezo	Twin piezo sounders with high decibel output
Visual alarm warning feature	In addition to the strobe which is present on all Deltabell Models, the Deltabell Plus will also strobe when the alarm is activated.

TECHNICAL SPECIFICATION

STROBE	
Strobe duration	10mS
Frequency	1Hz

CURRENT CONSUMPTION	
Standby	<60mA
Alarm - siren and Strobe	<300mA

DECIBEL	
Output	109dBA

ELECTRICAL	
Operating voltage	9-16VDC (12V nominal)