

IP Tranax 1700w Genmega 2500 setup

Go to Customer setup

go to change processor

change modem to **SSL Pass through**

Set on Standard 3

Enable SSL and change to TLS 1.2

Enable DCC and Reversal

Standard 3 option

Disable TCP/IPCRC and 12 Seq. #

Surcharge Mode

Enter Owner Name (CDS)

System Setup

Devise Setup

ATM TCPIP setup

Mode on **DHCP**

Then press **APPLY** button

Enter ATM Serial Number

Change Passwords use master 203040 and change service and operator also

Got to Host Menu

Host IP address

Change to 208.35.209.1

Change port to 6965

Host Set Up

(not needed on EMV upgrade)Key Management // password 000000 / 000000 **change password to 212121 for both**, Key mode change to // **TDES**, Key Index // **00**

Terminal ID /P for CDS

ATM routing ID // CDSAA0

Health Check // **Enable** Intervals // **8 hours**

Host Phone#s: if needed you will also need to change to Modem in step one

CDS (Ph1) **1866-923-3608** (Ph2) **1866-894-6184**

Settlement: Enter bill count