

VP5000

VHF · UHF (High & Low) · 700/800 MHz

P25 Phase 1 & 2 · Viking16

At just under 5.5 inches tall (140 mm), these small KENWOOD Viking portable radios are packed with advanced features for today's public safety agencies.

Features

- Mixed protocol operation (P25 Phase 1 & 2 Trunking, P25 Conventional, Viking16, FM Analog)
- Mixed protocol zones (each channel in a zone can be from a different system)
- 1024 channels
- 1 Watt audio output for high noise environments
- Voice annunciation & custom announcement creation
- Fully ruggedized - IP67 & MIL-STD-810 C/D/E/F/G
- Full key models (w/numeric keypad) & standard key models (w/o numeric keypad)
- Built-In GPS receiver/antenna for enhanced awareness¹
- MDC-1200 & GE-Star signaling
- P25 Authentication
- Bluetooth®
- Man Down
- Instant Recording Replay (IRR)
- Voice Recording
- Encryption
 - ARC4™ software encryption; compatible w/Motorola ADP™
 - DES-OFB
 - AES-256 (FIPS 140-2) Single and Multi-Key
 - Over-the-Air-Rekeying (OTAR)
 - VK5000 or Motorola KVL3000/KVL4000 Keyloader

Accessories

Complete line of accessories including microphones, speakers & antennas. Download the accessory catalog at www.efjohnson.com/products/accessories.




User Selectable Color Themes

- Multi-line text
- Multiple visual indicators including battery health & signal strength
- Day & night user selectable display options (8 themes available)



Day - High Contrast



Night - High Contrast

Compatible With P25 Systems

- ATLAS® P25 Phase 1 and Phase 2 System
- Motorola Astro® 25 - P25 Phase 1 & Phase 2
- Harris VIDA® - P25 Phase 1 & Phase 2
- Airbus (formerly Cassidian) VESTA™ Radio - P25 Phase 1 & Phase 2

We combine P25 design expertise with recognized quality & reliability along with advanced technology to make KENWOOD Viking radios simple to use & maintain.



Perpetual Software Licensing

Adds greater value to your radios by extending the life of the software into your next hardware platform — you own the software option forever, and your licenses are simple to manage with our cloud-based tool — Vault™.



Armada® Fleet Management

Update radios in a group rather than one at a time. One template programs both portables & mobiles. Supports either direct computer connection or Over-the-Air Programming (OTAP). Elite battery management enables wireless tracking of battery fleet.



TrueVoice™ Noise Cancellation

Software-based noise cancellation automatically filters out noise source frequencies and eliminates the need for extra configuration. Works in analog or digital mode and with any accessory.

VP5230/5330/5430 Portable Specifications

General		VP5230	VP5330	VP5430
Frequency Range		136-174 MHz (FCC ID K44431400)	Type 1: 450-520 MHz (FCC ID K44431500) Type 2: 380-470 MHz (FCC ID K44431501)	RX: 763-776, 851-870 MHz TX: 763-776, 793-806, 806-825, 851-870 MHz (FCC ID ALH442000)
Max. Channels Per Radio		1024		
Number of Zones		255		
Max. Channels Per Zone		255		
Channel Spacing	Analog	12.5/15/20/25*/30* kHz	12.5/25* kHz	12.5/25 kHz
	Digital	12.5 kHz	12.5 kHz	12.5 kHz
Power Supply		7.5 V DC ±20%		
Operating Temperature		-22 °F to +140 °F (-30 °C to +60 °C)		
Frequency Stability		±1.5 ppm	±1.5 ppm	±1.5 ppm
Dimensions (W x H x D) Projections Not Included	KNB-L2 (2,600 mAh)	2.28 x 5.47 x 1.56 in. (58.0 x 138.9 x 39.5 mm)		
	KNB-L3 (3,400 mAh)	2.28 x 5.47 x 1.77 in. (58.0 x 138.9 x 44.9 mm)		
Weight with Battery	KNB-L2 (2,600 mAh)	14.3 oz (406 g)		
	KNB-L3 (3,400 mAh)	15.8 oz (449 g)		
Receiver		VP5230	VP5330	VP5430
Sensitivity	P25 Digital (5% BER)	-119 dBm (0.025 µV)		
	Analog (12 dB SINAD)	-119 dBm (0.025 µV)		
Selectivity	P25 Digital	60 dB		
	Analog @ 12.5 kHz	65 dB		
	Analog @ 25 kHz	73 dB		
Intermodulation		73 dB		75 dB
Spurious Rejection		80 dB		75 dB
Audio Distortion		3%		
Audio Output Power		500 mW/8 Ω (3% Distortion)/1,000 mW/8 Ω (5% Distortion)		
Transmitter		VP5230	VP5330	VP5430
RF Output Power		1W/6W	1W/5W	1W/3W
Spurious Emission		-70 dB		
FM Hum & Noise	Analog @ 12.5 kHz	40 dB		
	Analog @ 25 kHz	45 dB		
Audio Distortion		2%		
Emission Designator		16K0F3E, 11K0F3E, 8K10F1E, 8K10F1D, 8K10F1W		16K0F3E, 14K0F3E, 11K0F3E, 8K10F1E, 8K10F1D, 8K10F1W

Mil Standard	810G
Low Pressure	500.5/ I, II
High Temperature	501.5/ I, II
Low Temperature	502.5/ I, II
Temp. Shock	503.5/ I
Solar Radiation	505.5/ I
Rain	506.5/ I, III
Humidity	507.5/ II
Salt Fog	509.5
Dust	510.5/ I
Vibration	514.6/ I
Immersion	512.5/ I
Shock	516.6/ I, IV

Encryption Options	
Supported Encryption	AES, DES-OFB, ARC4
Encryption Key/ Radio	126 Common Key Reference (CKR), 126 Physical Identifier, (PID), Compatible w/ Motorola Key Variable Loader
Encryption Frame Re-sync Interval	P25 CAI 360 MSEC
Encryption Keying	External Key Loader, OTAR
Mode	OFB-Output Feedback
Encryption Type	Digital
Key Erasure	Keyboard Command
Standards	FIPS 46-3, FIPS 81, FIPS 140-2, FIPS 197

Hazardous Location Certification	
Certification Lab	CSA Group
Standard Applied	ANSI/TIA 4950-A-2014, UL913 5th Edition & ANSI/ISA-12.12.01-2011
Classification Rating	Intrinsically Safe: Classes I, II, III, Division 1, Groups D, E, F, G Non-incendive: Class I, Division 2, Groups A, B, C, D
Approved Battery	KNB-LS7
Approved Speaker Micro-phones	KMC-54WDM
International Protection Standard	
Dust & Water	IP54, IP55
Immersion	IP67**/68***

*Refer to the Viking VP5000 operating manual for detailed requirements & conditions for proper GPS operation.

* 25/30 kHz in VHF/UHF Bands (except T-Band) are not included in the models sold in the USA or US territories.

** IP67/68 - Must have the Speaker Mic Universal Connector or Universal Connector Protector connected.

***IP68=1m/2H Specifications shown are typical and subject to change without notice Please check the website for the latest version. V.02.2519

© Copyright 2019 EF Johnson Technologies, Inc. (E.F. Johnson Company is operating entity) The Bluetooth word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc.

EF Johnson Technologies, Inc.

a JVCKENWOOD Company

1440 Corporate Drive, Irving, TX 75038-2401
Phone: 800.328.3911 · efjohnson.com