

- Built-in **VERBAL USER GUIDE**- access by pressing the **HELP** key or **PROG/HELP** on your phone. To hear an explanation of feature keys: press **HELP** or **PROG/HELP** then 0, dial 3 and press feature key. To exit this mode-press **PROG/HELP** or **HELP** button. (User help is also available at [www.esiusers.com](http://www.esiusers.com))

**LED Lamps**- Green indicates a function associated with your phone, red is someone else's

- ALL CALL PAGE**- Press Page(#), Press 0, Make Announcement
- To Check Voicemail- Press Voicemail Button (blinking). Prompts will follow.
- Transferring a call- Press TRANSFER, Press Station Key or dial station number, Make announcement, Hangup.
- Transferring a call directly to a mailbox- Press VOICEMAIL, Press Station Key, Hangup or (if no station key) Press VOICEMAIL, dial station number, Hangup.
- To leave a message in another mailbox- Press voicemail, Station key or press # plus exten no.
- Transfer caller to check messages- Press VOICEMAIL, hangup. Caller dial: \* plus extension.

\*\*\*\*\*

PRESS PROGRAM (48 key phone) or PROG/HELP (hear these prompts) PRESS 1 FOR MAILBOX GREETING, PRESS 2 TO PROGRAM STATION BUTTONS, 3 TO SET STATION OPTIONS, 4 TO ADJUST AUDIBLES, 5 FOR PASSWORD, 6 TO SET MESSAGE NOTIFICATION, **9 TO UNDELETE A MESSAGE**

**Above Programming Menu:** *Overview*

<b>1 Select personal greeting:</b> Choose greeting number or Press # for current greeting 1 Record 2 Delete 3 Hear	<b>2 Programmable feature keys</b> (Station keys, speed dials, other features)	<b>3 Station options</b> 1 Call waiting/background announce 2 Personal Greeting Reminder 4 Outside Dial Tone Preference 5 Hands free Answer 6 Message Monitor
<b>4 Station Audibles</b> 1 Station ring tone 2 Station ring volume 3 Message ring	<b>5 Password</b> 1 Enter 2 Delete 3 Hear 4 Security level	<b>6 External message notification</b> 1 Delivery Options 2 Phone delivery 3 Pager notification 4 Urgent Message 5 ESI Mobile Messaging
<b>7 Personal Call Routing</b>		<b>9 Un-delete Messages</b>

**Prog. Feature Keys** - User programmable keys on every phone can be set up for one button intercom calling with busy lamps, speed dial or for particular features you use the most. Just press a labeled button to activate the feature. **Press PROG/HELP 2 to set up your buttons.**

- To program an extension: press button, dial extension number, press button again.
  - To program a feature button: press button, press ESI-DEX twice and use the ^ scroll for feature, then STOR or press button, dial feature code, press button again.
    - For Caller-ID use Feature Code 574
    - For Headset use Feature Code 564
    - For Manual Day/Night use Feature Code 560
    - All Page Key use Feature Code # 0
  - To store a speed dial- press button, dial 9 plus the number, press button again.
  - To clear a button- press button, press hold, press button again
    - Virtual Mailbox Key- allows you to pick up others messages right from your phone.
- To program: Press button, press VOICEMAIL, dial extension number, press button again.

**Off Premise Call Forward:**

- press CFWD, Dial 9+number, press #
- press CFWD, \* to cancel

**How to program a guest mailbox:** press PROGRAM, press \*, dial box no., then #, password, #

**Program your Personal Greeting:**

- Press Program then 1(For Personal Greeting)
- Press # to confirm or select 1,2 or 3 for a specific greeting then #
- Press 1 to Record and follow the prompts

## Personal Speed Dial Programing

### 48 Key Phone:

Press ESI-DEX (under display)

Press PER

Press NEW

Use the dial pad keys to enter the letters to spell the name of the number you are storing.

(Example: Use the 5 button for the letters JKL. Press it once for J, twice for K or 3 times for L)

Press “#” key after each letter to save the entry. When the name is complete press “#” to skip to the next step.

Enter 9 (dial access code) plus the phone number you are storing. Press # to save the number.

Example: to store 1-800-123-4567 you will enter 918001234567

Press STOR

### TO CALL OUT:

Press ESI-DEX

Press PER (for personal) \*

Press scroll keys or dial the first the letters of the name you are search for, if you have more than one entry that starts with the same first 3 digits you may have to use the scroll keys to finalize your search.

(Example: To search for John you would Dial 5,6,4)

Press DIAL to make the call

\* (SYS=System speed dials/ STA= Interoffice extensions/LOC=ESI-Link Locations)