

## Multi-element Analyzer for Inelastic X-ray Scattering

W.A. Caliebe<sup>1</sup>, Q.J. Qiang<sup>2</sup>, T.A. Tyson<sup>2</sup>, B. Blank<sup>3</sup>, A. Deyhim<sup>3</sup>, C.-C. Kao<sup>1</sup> <sup>1</sup>National Synchrotron Light Source, BNL, Upton NY 11973 <sup>2</sup>Department of Physics, NJIT, Newark, NJ <sup>3</sup>Advanced Design Consulting, Lansing, NY

**Rowland-circle Spectrometer** 



# Inelastic X-ray scattering and the second second

Spherical Aberration



Backscattering: point-to-point focusing smaller Bragg-angles point-to-line focusing size depends on analyzer size perpendicular to scattering plane and on Bragg angle (see figure)

#### Spin-polarized XANES



Spin-resolved XANES spectra of  $Pr_{0,3}Ca_{0,7}MnO_3$  for the spin-down (thick line) and spin-up (thin line) channels. The splitting of the main edge is due to the spin asymmetry of the different Mn sites. Spectra were measured with only six analyzers. Analyzer Rostandcircle Smirze Decise

#### Mount source, analyzer and detector on circle with diameter r, radius of analyzer r: All rays emitted from source hit analyzer under the same angle, if the

angle is close to backscattering, and if the size is not too large compared to the size. Variations: Use cylindrically bend analyzer, with the axis parallel or perpendicular to the scattering plane, dispersion allows to measure larger energy range.



#### Applications of Inelastic Scattering

- •High-resolution spectroscopy (meV and less)
- •Phonon excitations at low momentum transfer (not accessible by inelastic
- neutron scattering)
- •Medium-resolution spectroscopy (sub-eV)
- Electronic excitation
- •valence band excitations (non-resonant)
- •Non-resonant Raman scattering (absorption spectroscopy of soft x-ray edges with hard x-rays)
- •Resonant Raman scattering ('improve' the energy resolution in the nead-edge region), spin-resolved spectroscopy

Acknowledgment: Financial Support for this project by the NSF under Contract No. 0216858 is greatly appreciated. Research carried out at NSLS, Brookhaven National aboratory, which is supported by the U.S. Department of Energy, Office of Basic Energy Sciences, under Contract No. DE-AC02-98CH10886.

## **Energy Resolution**

- Intrinsic resolution
- •Johann geometry
- •Bragg angle
- •Source size •Size of analyzer



•Deviation of Rowland geometry

•Bending radius of analyzer or size of individual rectangles

### How to make spherically-bent Analyzers



Apply thin layer of epoxy on mirror
Carefully lay wafer on mirror
Jay greased mirror-paper on wafer
Place die on paper
Apply pressure and bent the crystal
Gwait a long time (twice the curing time)
Release pressure and check mirror



Typical Problems 'Too much epoxy 'Dust-particles (clean room!) 'Compression of surface cause ripples



NATIONAL LABORATORY