



Scentry III-GFRAB

Application

The **Scentry III-GFRAB** Home Gas Detector is designed to sense the presents of explosive gases. Once an explosive gas has been detected this model will sound an alarm and activate equipment to remove dangerous gas build up in a building. This series of products offered by Safety First USA, Inc. has been designed for ease of installation and reliable service. This product has easily accessible terminal strips for fast and secure wire connections, backup battery charging, low battery detect and sensor failure alarm.

Product Specifications

Case	ABS plastic
Size	7.6" X 4.6"
Weight	2.25 lbs
Color	Gray
Power Consumption	1.5va
Connections	Screw Terminals
Input Power	115VAC 60 Hz
Output Control Relays	2 amp 24vac
Alarm Signal Output	12 Vdc @ 500ma.
Reset	Manual
Sensor Type	tin dioxide semiconductor

Alarm Points

Propane (LP)	<5200 PPM
Natural Gas / Methane	<12,200 PPM



Model	Options				
Scentry III-	G	F	R	A	B
	Gas	Mounting Feet	Remote Ready	Alarm	Backup Battery

Made in USA

Safety First USA, Inc.

3229 English Cove Lane, Marion, Iowa 52302-7608
 Phn 319-377-1129 • Fax 319-377-1539 • Info@SafetyFirstUSAInc.com