

## by Honeywell

### Description

The Gamewell-FCI, PM-9 Power Supply is a switching power supply that provides 9 amperes of filtered and regulated 24 VDC (nominal). It provides the power to the INX Transponder assembly and all of the E3 Series components. It is a component of the following systems.

- E3 Series<sup>®</sup> Expandable Emergency Evacuation System
- E3 Series Combined Fire and Mass Notification System
- E3 Series Broadband Voice Evacuation System
- NetSOLO<sup>®</sup> System

The PM-9 has an internal battery charging circuit capable of maintaining up to 55 A/H batteries. This module is designed for use with the Gamewell-FCI distributed audio networks.

#### Installation

Typically, the PM-9 Module can be mounted in the following E3 Series cabinets:

- Cabinet B and D, backbox
- Cabinet C, INX-E3 sub-assembly plate
- Cabinet C, INCC-E3 sub-assembly plate
- Cabinet D, E3-INX-D Plate
- Cabinet D, E3-ILI-D Plate

For information on the installation of the PM-9, refer to the following documents:

- E3 Series Expandable Emergency Evacuation Manual, P/N: LS10080-000GF-E
- PM-9 Installation Instructions, P/N: 9000-0548
- Mass Notification System Manual, P/N:LS10013-000GF-E

### **Specifications**

Input Voltage:	120 VAC 60 Hz @ 3.5 A. max.
Output Voltage:	24 VDC (nominal) FWR
Output Current:	9 amperes
Output Current:	1 ampere battery charging
	current
Alarm Current:	0.050 amp
<b>Operating Temperature</b>	: 32° to 120° F (0° to 49° C)
Relative Humidity:	0 to 93% (non-condensing) at
	90° F (32° C)
Dimensions:	10 1/2" W x 5" H x 2" D
	(27 x 13 x 5 cm)

 $\text{E3\,Series}^{\textcircled{0}}$  and  $\text{NetSOLO}^{\textcircled{0}}$  are registered trademarks of Honeywell International Inc. UL is a registered trademark of Underwriter's Laboratories Inc.

# **PM-9**

### PM-9 Power Supply



PM-9

### **Features**

- Listed under UL<sup>®</sup> Standard 864, 9th Edition.
- Listed under UL Standard UL2572 for Mass Notification.
- Includes 9 ampere, filtered, regulated power supply.
- Provides 1 ampere battery charging current.
- Offers energy and space saving switching technology.
- Contains an integral battery charger capable of recharging up to 55 AH batteries. (Batteries not furnished).

### **Ordering Information**

Part Number	Description
РМ-9	Power supply
29229	AC Line Filter Kit



GAMEWELL-FCI Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use. ©2015 by Honeywell International Inc. All rights reserved. WWW.gamewell-fci.com 9020-0555 Rev. P page 1 of 1