

## 131-36 series

### DC Desktop Type Power Adapter – 36V 1A/ 2A/ 3A/ 4.16A



#### FEATURES

- Input Voltage: 100-240VAC 50/60Hz
- Output Power: 36VDC, 1A/ 2A/ 3A/ 4.16A
- DC Plug: 5.5 x 2.5/ 2.1mm
- DC Output Polarity: Centre Positive
- LED Optical Signalization
- Protection: Short-circuit/ Over-voltage/ Over-load
- Anti-interference Magnetic Ring to avoid EMI (Electromagnetic Interference)

#### SPECIFICATIONS

|                        |                       |
|------------------------|-----------------------|
| Input Voltage          | 100-240VAC            |
| Frequency              | 50-60Hz               |
| Output Voltage         | DC36V                 |
| Output Current         | 1A/ 2A/ 3A/ 4.16A     |
| Efficiency             | 80% Typ.              |
| Ripple & Noise         | 120mVp-p Typ.         |
| Color                  | Black, Plastic molded |
| Application            | Indoor                |
| Power Cord Type        | IEC60320-C13          |
| Operation Temperature  | 0°C to +40°C          |
| Dimensions (L x W x H) | 125 x 54 x 32mm       |
| Weight                 | 240g                  |
| Length of DC Cable     | 1.1m                  |

#### ORDERING INFORMATION

|           |                            |
|-----------|----------------------------|
| 131-3610A | DC Power Adapter 36V 1A    |
| 131-3620A | DC Power Adapter 36V 2A    |
| 131-3630A | DC Power Adapter 36V 3A    |
| 131-3640A | DC Power Adapter 36V 4.16A |