

## PA3010

### DC Wall Mount Power Adapter – 12V, 1A

This 12V DC power supply can provide a power source for any electronic device that has a DC5.5 x 2.5/2.1mm center positive barrel plug and the unit is protected against short-circuit and overload.

When connected to DC power splitter cables AC-902, the power supply unit can feed 2 cameras simultaneously.

Also, it is a perfect replacement for the lost or damaged power adapter you have used to power your existing electronics, such as: LED strips lights, cable modem/ router/ electronic piano keyboard/ DVR & NVR surveillance system/ security CCTV camera/ infrared IR array illuminator and other 12VDC devices.



#### FEATURES

- Input Voltage: 100-240VAC 50/60Hz
- Output Power: 12VDC, 1A
- DC Plug: 5.5 x 2.5/ 2.1mm
- DC Output Polarity: Centre Positive
- LED Optical Signalization
- Protection: Short-circuit/ Over-voltage/ Over-load

#### SPECIFICATIONS

Input Voltage	100-240VAC
Frequency	50-60Hz
Output Voltage	DC12V
Output Current	2A
Efficiency	78% Typ.
Ripple & Noise	80mVp-p Typ.
Color	Black, Plastic molded
Application	Indoor
Operation Temperature	0°C to +40°C
Dimensions (L x W x H)	75 x 40 x 38mm
Weight	70g
Length of DC Cable	1.0m

#### ORDERING INFORMATION

PA3010/UK	[ESS] DC Power Adapter 12V 1A, UK plug
PA3010/US	[ESS] DC Power Adapter 12V 1A, US plug
PA3010/EU	[ESS] DC Power Adapter 12V 1A, EU plug
PA3010/AUS	[ESS] DC Power Adapter 12V 1A, AUS plug