

# **Radio Interface Cable**


For NCS-C250 Mobile Multi-Switcher

**NCS Model Number** 

# NCS-250-KKA-XX


### **Compatible Radios:**

TK-760 TK-860



#### **RJ-45** Pin # Wire Color **Function** White Mic Hi 2 Green Mic Lo PTT 3 Brown 4 Black Ground Rx Audio 5 Yellow 6 Shield Ground Hook Sw\* Red COR\* Orange

\*Active only if Switch Hook or COR Option installed.



## **Cable Wiring**

### Note:

- 1. Radio must have the Kenwood KCT-19 Accessory Cable installed in order to interface to the NCS-250-KKA-XX cable.
- 2. To connect the COR signal to pin 13 of the KCT-19 ACC connector, solder the two anodes of D205 together. Refer to the radio's service manual for the location of this diode.