



- A. Assemble the AS-40018 post, AWD-3213 top rail, AWD-2201 mid rail, and AS-40022 roof brace as shown.
- B. Secure all in place with five (5) 5/16" Flange Bolts and five (5) 5/16" Lock Nuts.
- C. Repeat for the opposite side.

DRAWN Marcus Wilmsmeyer 6/25/2018	Greene Galvanized Stairs				
CHECKED	East Lynn, IL 217.375.4244				
OA	www.greenebinstairs.com				
MEG	TITLE				
MFG	ANATE 4 450 A LL T L L'				
APPROVED	AWT51450 Assembly Instructions				
	-				
	SIZE DWG NO REV				
	A IN-AWT51450				
	SCALE 1/12 SHEET 2 OF 4				



- A. Position the ES-5015 brace on the roof ribs such that it will not interfere with the Manhole Guardrail assembly and an opened or closed manhole hatch.
- B. Secure to the roof using two (2) 3/8" bolts and two (2) 3/8" Lock Nuts.
- C. Attach the two siderail assemblies built in the previous step to the ES-5015 roof mount. Secure in place using two (2) 5/16" Flange Bolts and two (2) 5/16" Lock Nuts.

DRAWN Marcus Wilmsmeyer	6/25/2018		Greene Galva		
CHECKED			East Lynn, IL 2		
QA		www.greenebinstairs.com			
MEG		TITLE			
MFG		A \ A (TTT = 1 /	I = 0 A		.
APPROVED		AW 1514	150 Assen	nbly Instruct	ions
				•	
		SIZE	DWG NO		REV
		A	IN-AV	/T51450	
		SCALE 1/15		SHEET 3 OF 4	



- A. Attach the two AS-40018 posts to the matching posts on the inside of the AWT8644 platform, using four (4) 5/16" Flange Bolts and four (4) 5/16" Lock Nuts.
- B. Assemble the AS-40023 bracket, AS00030 Step Tread, and AS-40024 bracket together, using four (4) 5/16" Flange Bolts and four (4) 5/16" Lock Nuts.
- C. Secure the booster step assembly to the bin wall using four (4) Bin Bolts and four (4) Lock Nuts.
- D. Secure handrails TR150536 and AS-40011 to the assembly using four (4) HRC1500 handrail clamps and four (4) 5/16" Flange Bolts and four (4) 5/16" Lock Nuts.

DRAWN Marcus Wilmsmeyer 6/25/2018	Greene Galvanized Stairs			
CHECKED	East Lynn, IL 217.375.4244			
QA	www.greenebinstairs.com			
MFG	TITLE			
INFG	A)A/TE4 4E0 A			
APPROVED	AWT51450 Assembly Instruction	ns		
	SIZE DWG NO IN-AWT51450	REV		