

Introducing The

MINI **3**

Two-way Radio



approximate size

The **MINI 3** is small, lightweight, easy to carry and user friendly. This small radio is robust with features such as 16 channels, high/low power settings, scan, battery save mode, wireless cloning and a proceed-to-talk tone.

FEATURES:

- **Small - only 4.75" tall**
(including antenna)
- **Light - only 2.4 oz.**
- 16 Channels
- Companding
- **NEW** - Channel Scan
(Optional with user selectable by channel)
- **NEW** - Strong Accessory Jack
- **NEW** - User Menu (if enabled) with four programmable settings
- Single Board Design
- **NEW** - Wireless Cloning
- **NEW** - Adjustable Microphone Sensitivity
- Same accessories as the MINI, and MINI 2 two-way radios
- **NEW** - GREAT LOW PRICE!

MINI 3

Two-way Radio



SPECIFICATIONS:

Dimension (inches)	
Height	4.75
Width	1.625
Depth	0.75
Weight (w/battery & antenna)	2.4 ounces
Antenna	Fixed
Audio Accessory Jack	Single Pin
Power Supply - Battery	Li-Ion 3.7V 800 mAh
Power	1 W
Channels	up to 16
Select Channels	Up/Down Buttons
Frequency	450-470MHz UHF Band
Battery Status Indicator	Yes
Built-in VOX	Yes
Battery Save Mode	Yes (User Selectable On/Off)
TOT	Yes
Companer	Yes / Channel
Scan	Yes - Add/Delete
Busy Channel Lock-Out	Yes
Proceed to Talk Tone	Yes
Scramble	Yes
LCD	Yes - with Back Light
Temporary Local Audio Reduction	Yes
CTCSS & DCS Coding	Yes
User Programmable/Selectable	4 Items: <ul style="list-style-type: none"> • Battery Save Mode • High/Low Power • Push-to-Talk Proceed Tone • Scan, Channel Add/Delete
Keylock	Yes
Adjustable Microphone Gain (Sensitivity)	Yes
Wireless Cloning	Yes

Items in **red** are new to the MINI 3.

Some Available Accessories



Holster Swivel
20-9241



Armband
20-9586



Magnet Clothing Mount
20-9722



Six-unit Gang Charger
20-8640



Plug-in Charger
20-9265



Break-a-way Lanyard
20-9906

follow us on:



(952) 469-5400
20809 Kensington Blvd., Lakeville, MN 55044
www.advancedwireless.com